



SCHMATIC
FUSE RECOMMENDED
BUT NOT SUPPLIED

++ LINE TO LINE VOLTAGE

⚡ IF GANGED UNITS ARE USED IN A SYSTEM THAT ORDINARILY HAS A COMMON NEUTRAL OR GROUND BETWEEN SOURCE AND LOAD, THE NEUTRAL OR GROUND MUST BE CONNECTED TO THE COMMON TERMINALS OF THE VARIABLE TRANSFORMER ASSEMBLY. IF THE SYSTEM HAS NO NEUTRAL, THE LOAD MUST BE BALANCED OR THE TRANSFORMERS WILL BE DAMAGED.

■ JUMPER PROVIDED IN THE STANDARD COMMON POSITION AND SHOULD BE MOVED OR REMOVED AS REQUIRED.

| SPECIFICATIONS | | | | | | | | | | | |
|-------------------|-------|-------|--------|-----------------------|----------|-------------------------|------------------------------------|--|-------|--------|--------|
| WIRING | INPUT | | OUTPUT | | | | SHAFT ROTATION TO INCREASE VOLTAGE | TERMINAL CONNECTIONS | | | |
| | VOLTS | HERTZ | VOLTS | CONSTANT CURRENT LOAD | | CONSTANT IMPEDANCE LOAD | | FOR INCREASING VOLTAGE AS VIEWED FROM BASE END | | | |
| | | | | MAX. AMPS | MAX. KVA | MAX. AMPS | | MAX. KVA | INPUT | JUMPER | OUTPUT |
| THREE PHASE WYE ⚡ | 240 | 60 | 0-240 | 2.0 | 0.83 | 2.5 | 1.04 | CW | 2-2-2 | 1-1-1 | 3-3-3 |
| | ++ | | | | | | | CCW | 1-1-1 | 2-2-2 | 3-3-3 |

| | | | | | | | | | | |
|---|-------|--------|--------|------------------------------------|--|------------------------------|--|-------------------------|--|-------------------|
| UNLESS OTHERWISE SPECIFIED, TOLERANCE IS ± | | | | UNITS | | TITLE: SPEC. CONTROL DRAWING | | | | |
| DECIMALS | HOLES | ANGLES | DRAFT | IN [mm] | | VARIABLE TRANSFORMER | | | | |
| .XX | .014 | 1° | 1-1/2° | | | TYPE: 201-3 | | | | |
| .XXX | .005 | | | ALL DIMENSIONS APPLY AFTER PLATING | | DRAWN BY: TIM RAU | | | | |
| MATERIAL: | | | | | | DATE: 6/6/02 | | FIRST USED ON: | | DO NOT SCALE DWG. |
| The information and design disclosed herein was originated by and is the property of STACO ENERGY PRODUCTS CO., which reserves all patent, proprietary, design, manufacturing, reproduction, use and sale rights thereto, and to any article disclosed therein except to the extent rights are expressly granted to others. The foregoing does not apply to vendor proprietary parts. | | | | | | CHECKER: | | WEIGHT APPROX. 6.5 LBS. | | CAGE CODE 83008 |
| | | | | | | ENGINEER: | | SCALE 1=1 | | SHEET 1 OF 1 |

